

ZERO RUNNER

COMPARE SPECIFICATIONS

	ZR6	ZR7	ZR8000	ZR7000
Key Mechanical Features				
User defined running motion	•	•	•	•
Dynamic stride length	58" (147cm)	58" (147cm)	58" (147cm)	58" (147cm)
Aluminum Legs	•	–	•	–
Lightweight pedals	•	–	•	–
Tablet/reading rack	•	•	Smart Console only	Smart Console only
Phone holder	–	–	•	•
Performance resistance range	•	–	15 resistance levels	10 resistance levels
CROSS CIRCUIT attachment points	7	7	–	–
Set of CROSS CIRCUIT resistance bands	•	•	–	–
CROSS CIRCUIT Pro compatible	–	–	•	•
Pedal spacing	1.4" (3.5cm)	2.0" (5.1cm)	1.5" (3.81cm)	1.5" (3.81cm)
Low step-up height	5.2" (13.2cm)	5.2" (13.2cm)	5.2" (13.2cm)	5.2" (13.2cm)
Rubber non-slip pedals	•	•	•	•
Rubber non-slip step	•	–	•	•
Moving handlebars	Contoured grip	Standard	Contoured grip	Standard
Performance grips	•	–	–	–
Water bottle holder	1	1	2	2
Whisper quiet operation	•	•	•	•
Transport wheels	•	•	•	•
Heavy-duty frame	•	–	–	•
Electronic Features				
SmartLink Compatible	•	•	–	–
Bluetooth® 4.0 for mobile device connectivity	•	•	–	–
Head up display	•	•	•	•
Self-powered*	•	•	Standard Console only	–
Quick Start (Run)	•	•	•	•
Cool down	•	•	•	•
Wireless heart rate compatible**	Polar®, ANT+, Bluetooth 4.0	Polar®, ANT+, Bluetooth 4.0	Polar®, ANT+	Polar®, ANT+
Digital contact heart rate sensors	•	•	•	•
Polar heart rate chest strap	–	•	–	–
Bluetooth 4.0 / ANT+ heart rate chest strap	•	–	–	–
Workouts				
Number of programs on console	4	4	8†	8†
Number of Workouts with SmartLink				
Endurance programs Race training, pace intervals	14	14	8††	8††
Tone up programs Strength training, targeted muscle groups	12	12	6††	6††
Active recovery programs Flexibility, Run+, balance	10	10	6††	6††
Product Specifications				
Max user weight	300lbs (136Kg)	300lbs (136Kg)	400lbs (181Kg)	400lbs (181Kg)
Footprint – live area (W x L)	38" x 63" (97 x 160cm)	38" x 63" (97 x 160cm)	43.2" x 69.6" L (110 x 176cm)	43.2" x 69.6" L (110 x 176cm)
Product weight	191lbs (87Kg)	195lbs (89Kg)	357lbs (162Kg)	344lbs (156Kg)
Warranty				
Frame	Lifetime	Lifetime	Lifetime	Lifetime
Parts	5 Years	5 Years	5 Years	5 Years
Labor	1 Year	1 Year	1 Year	1 Year

* ZR6 and ZR7 include 4 AA batteries for console operation

** ZR6 and ZR7 Bluetooth 4.0 connection requires iPad running SmartLink app

† Programs available on ZR8000 and ZR7000 Standard Console

†† Programs available on ZR8000 and ZR7000 Smart Console – not compatible with tablet version of SmartLink app